

STROBE-BRIK™

Stand-alone 14W LED Fire Cube Configurable LED fixture

The **powerful and compact** stand-alone 14W Fire Cube fixture may be configured as a strobe, dimmer, mini-wall washer or fiber-optic illuminator. Optical and mounting options make the system perfect for club, effect, or architectural applications. The Fire Cube uses high quality Luxeon Rebel LEDs, providing some of the highest efficacies available.

Applications

- Casinos
- Theme park attractions
- Effect lighting
- Museum showcases
- Fiber optic applications

Features

- No external controller or DMX required.
- Selectable modes:
 - √ Single-channel dimmer
 - √ Variable rate full-power color changing
 - √ Variable rate multi-color auto fade
 - √ Variable rate all-channel full-power strobe
- Anodized solid aluminum integrated heat sink.
- Low-voltage use with external power supply.
- Mounting and lens options.



Available LED colors

COLOR	Lumens@700mA
RED	340
GREEN	580
BLUE	232
CYAN	520
AMBER	520
RED-ORANGE	400
COOL WHITE	720
NEUTRAL WHITE	308
WARM WHITE	720
RGGB	Red: 85, Grn: 145, Blu: 58
RGBA	Red: 85, Grn: 145, Blu: 58, Amber: 130

Specifications

- 14W @750mA
- 3" X 3" X 3" cube
- 50,000 hrs life at 750mA with 70% lumen maintenance.